

## Red Sensor Temperature To Resistance Chart

Deg F	Deg C	Ohms	Deg F	Deg C	Ohms
32	0	105.2K	87.8	31	22.9K
33.8	1	99.6K	89.6	32	21.9K
35.6	2	94.4K	91.4	33	21.0K
37.4	3	89.8K	93.2	34	20.1K
39.2	4	84.8K	95	35	19.2K
41	5	80.4K	96.8	36	18.4K
42.8	6	76.3K	98.6	37	17.6K
44.6	7	72.4K	100.4	38	16.9K
46.4	8	68.7K	102.2	39	16.2K
48.2	9	65.3K	104	40	15.6K
50	10	62.0K	105.8	41	14.9K
51.8	11	59.0K	107.6	42	14.3K
53.6	12	56.1K	109.4	43	13.7K
55.4	13	53.3K	111.2	44	13.2K
57.2	14	50.7K	113	45	12.7K
59	15	48.3K	114.8	46	12.2K
60.8	16	46.0K	116.6	47	11.7K
62.6	17	43.8K	118.4	48	11.2K
64.4	18	41.7K	120.2	49	10.8K
66.2	19	39.8K	122	50	10.4K
68	20	37.9K	123.8	51	10.0K
69.8	21	36.1K	125.6	52	9.61K
71.6	22	34.5K	127.4	53	9.25K
73.4	23	32.9K	129.2	54	8.90K
75.2	24	31.4K	131	55	8.57K
77	25	30.0K	132.8	56	8.25K
78.8	26	28.7K	134.6	57	7.94K
80.6	27	27.4K	136.4	58	7.65K
82.4	28	26.2K	138.2	59	7.37K
84.2	29	25.0K	140	60	7.10K
86	30	23.9K	141.8	61	6.85K